



Fused Technology, Inc.
440 Waters Watch Court
Baltimore, MD 21220
(410) 670-7200

How to configure a factory default Aastra Phone for use with the FTI PBX Phone Service

1. Before this can be done, the phone MUST be associated on the client's FTI PBX Servers. Please verify from FTI support that the phone is already associated on the servers prior to completing these steps.
2. Plug a standard Cat-5 Cable from the 'LAN' port on the phone into the FTI Voice PoE Ethernet switch. (or plug into any network with the A/C power adapter if supplied)
3. Allow the phone to boot up fully.
4. Press the Options button on the Phone
5. Press the Number keys 3 then 1. (Note: For Aastra models 30i/31i/53i, you must press the right arrow '►Enter' on the phone after pressing 3)
6. This will display the IP address of the Phone. If its is on an FTI supported network, the IP address should be 10.20.10.x. If it is on another network, it might be something like 192.168.0.x
7. Make note of the IP address.
8. From a computer on the same network as the phone, (or has access to the phone network), open a Internet browser, and type in the IP Address of the Phone in the address bar. i.e. <http://10.20.10.61>
9. The default username is admin and the default password is 22222
10. Click on the 'Configuration Server link' in the lower Left hand side of the screen
11. On the right hand side, change the 'Download Protocol' to FTP
12. Type in cfg.fusedtech.com in the 'FTP Server' field.
13. Type in your PBX context, which can be obtained from FTI support, in the 'FTP Username' Field.
14. Type in the password obtained from FTI Support.
15. Scroll down, and click on the Save Settings Button.
16. Now reboot the phone, this can be done by clicking on the Options button on the phone, then the number 6 on the keypad, then 'Restart.' . (Note: For Aastra models 30i/31i/53i, you must press the right arrow '►Enter' on the phone after pressing 6, then press # to Confirm)
17. Please note upon restart, it will download new firmware/configuration settings, and might reboot its self several times.

See next page for image.

Aastra 6731i - Windows Internet Explorer

http://10.20.10.61/configurationServer.html

File Edit View Favorites Tools Help

Aastra 6731i

AASTRA

Status

- System Information

Operation

- User Password
- Phone Lock
- Programmable Keys
- Keypad Speed Dial
- Directory
- Reset

Basic Settings

- Preferences
- Account Configuration

Advanced Settings

- Network
- Global SIP
- Line 1
- Line 2
- Line 3
- Line 4
- Line 5
- Line 6
- Action URI
- Configuration Server
- Firmware Update

Configuration Server Settings

Settings	
Download Protocol	FTP ▼
TFTP Server	192.168.0.16
TFTP Path	
Alternate Server	0.0.0.0
Alternate TFTP Path	
Use Alternate TFTP	<input type="checkbox"/> Enabled
FTP Server	→ cfg.fusedtech.com
FTP Path	
FTP Username	→ ftiabc
FTP Password	→ ●●●●●●
HTTP Server	
HTTP Path	
HTTP Port	80
HTTPS Server	
HTTPS Path	
HTTPS Port	443